

# electro-harmonix

## **SATISFACTION** **VINTAGE FUZZ**

Congratulations on your purchase of the Satisfaction Fuzz, a modern recreation of the classic fuzz sounds of the 1960s. Updated with a compact nano chassis, the Satisfaction creates drive sounds ranging from crunchy breakup to intense fuzz. Attack and Volume controls put you in the mix, and true-bypass switching keeps your bypassed signal intact

### **- CONTROLS -**

**ATTACK Knob** – Controls the amount of input gain and distortion. As you turn this knob clockwise, the SATISFACTION ranges from mild drive to saturated fuzz.

**VOL Knob** – Sets the output level of the SATISFACTION.

**FOOTSWITCH and LED** – The Footswitch selects whether the SATISFACTION is engaged or in true bypass mode. When the effect is engaged, the LED is lit.

**INPUT Jack** – This ¼" jack is the audio input for the SATISFACTION. The input impedance is 50kΩ.

**AMP Jack** – This ¼" jack is the audio output from the SATISFACTION. The output impedance depends on the VOLUME setting, ranging from 100Ω to 25kΩ.

**9V Power Jack** – The SATISFACTION can run off of a 9V battery or you can use an optional 9VDC AC Adapter capable of delivering at least 25mA to the 9V power jack. We recommend the **EHX9.6DC-200**. The AC Adapter must have a center negative plug. The battery may be left in or taken out when using an AC Adapter. The SATISFACTION draws 1.5mA at 9VDC. **The maximum voltage that may be connected to the 9V Power Jack is 10VDC.**

### **- CHANGING THE BATTERY -**

To change the battery, remove the four screws on the bottom of the SATISFACTION and take off the bottom plate. The battery clip is in the bottom of the unit. Take care not to touch the circuit board while changing the battery in order to avoid damaging a component.

## - WARRANTY INFORMATION -

Please register online at <http://www.ehx.com/product-registration> or complete and return the enclosed warranty card within 10 days of purchase. Electro-Harmonix will repair or replace, at its discretion, a product that fails to operate due to defects in materials or workmanship for a period of one year from date of purchase. This applies only to original purchasers who have bought their product from an authorized Electro-Harmonix retailer. Repaired or replaced units will then be warranted for the unexpired portion of the original warranty term. If you should need to return your unit for service within the warranty period, please include a brief description of the problem as well as your name, address, telephone number, copy of your receipt, and a check or money order.

**United States - \$12**

**Canada - \$15**

**Europe and outside countries - \$25**

**Ship to:**

Electro-Harmonix  
C/O New Sensor Corporation  
55-01 2nd Street  
Long Island City, NY, 11101

**Attn:** Service Department

Please make checks/money orders **payable to New Sensor Corporation.**

To hear demos on all EHX pedals visit us on the web at **[www.ehx.com](http://www.ehx.com)**

Email us at **[info@ehx.com](mailto:info@ehx.com)**

